



ASSEMBLER PROGRAMMERS REFERENCE MANUAL PART 2

APPENDIX E EBCDIC CHARACTER SET

		00				01				10				11				Bits 0.1	
Bits 4567	Hex 1	00	01	10	11	00	01	10	11	00	01	10	11	00	01	10	11	2.3	Hex C
		0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F		
0000	0	NUL	DLE			SP	&	'	0	SP	&	'	0	SP	&	'	0		
0001	1	SOH	SBA			A	J	/	1	a	j	/	1	A	J	/	1		
0010	2	STX	EUA		SYN	B	K	S	2	b	k	s	2	B	K	S	2		
0011	3	ETX	IC			C	L	T	3	c	l	t	3	C	L	T	3		
0100	4					D	M	U	4	d	m	u	4	D	M	U	4		
0101	5	PT	NL			E	N	V	5	e	n	v	5	E	N	V	5		
0110	6			ETB		F	O	W	6	f	o	w	6	F	O	W	6		
0111	7			ESC	EOT	G	P	X	7	g	p	x	7	G	P	X	7		
1000	8					H	Q	Y	8	h	q	y	8	H	Q	Y	8		
1001	9		EM			I	R	Z	9	i	r	z	9	I	R	Z	9		
1010	A					⊘	!		:	⊘	!		:	⊘	!		:		
1011	B					·	\$	,	#	·	\$	,	#	·	\$	,	#		
1100	C	FF	DUP		RA	<	'	%	@	<	'	%	@	<	'	%	@		
1101	D		SF	ENQ	NAK	(	)	_	'	(	)	_	'	(	)	_	'		
1110	E		FM			+	;	>	=	+	;	>	=	+	;	>	=		
1111	F		ITB		SUB		⌋	?	"		⌋	?	"		⌋	?	"		

 : To be used for national characters  
 Characters within the white positions are translated to /00.

 : Characters used for IBM 3270 Test Request messages.  
 Normally they are not used.